

SPECIFICATIONS																			
OUTPUT MODE	Voltage Current Tracking Series Voltage Tracking Parallel Current	GPS-4303				GPS-4251				GPS-3303			GPS-2303						
		CH1	CH2	CH3	CH4	CH1	CH2	CH3	CH4	CH1	CH2	CH3	CH1	CH2					
		0 ~ 30V		2.2 ~ 5.2V		8 ~ 15V		0 ~ 25V		3 ~ 6V		8 ~ 15V		0 ~ 30V		5V Fixed		0 ~ 30V	
		0 ~ 3A		1A Max.		1A Max.		0 ~ 0.5A		2.5A Max.		1A Max.		0 ~ 3A		3A Max.		0 ~ 3A	
		0 ~ 60V		----				0 ~ 50V		----				0 ~ 60V		----		0 ~ 60V	
		0 ~ 6A		----				0 ~ 1A		----				0 ~ 6A		----		0 ~ 6A	
CONSTANT VOLTAGE OPERATION (CH1, CH2)	Line Regulation	≤ 0.01% + 3mV																	
	Load Regulation	≤ 0.01% + 3mV (rating current ≤ 3A) ≤ 0.02% + 5mV (rating current > 3A)																	
	Ripple & Noise	≤ 1mVrms , 5Hz ~ 1MHz																	
	Recovery Time	≤ 100 μ S (50% Load change, Minimum load 0.5A)																	
CONSTANT CURRENT OPERATION (CH1, CH2)	Line Regulation	≤ 0.2% + 3mA																	
	Load Regulation	≤ 0.2% + 3mA																	
	Ripple & Noise	≤ 3mArms																	
TRACKING OPERATION (CH1, CH2)	Tracking Error	≤ 0.5% + 10mV of the CH1																	
	Series Regulation	≤ 300mV																	
	Load Regulation	≤ 0.01% + 3mV																	
	Ripple & Noise	≤ 2mVrms , 5Hz ~ 1MHz																	
GPS-4303 2.2V ~ 5.2V OUTPUT (CH3) GPS-3303 5V FIX OUTPUT (CH3) GPS-4251 3V~6V OUTPUT(CH3)	Line Regulation	≤ 5mV																	
	Load Regulation	≤ 15mV																	
	Ripple & Noise	≤ 2mVrms, 5Hz ~ 1MHz																	
	Current Output	GPS-4303: 1A, GPS-3303: 3A, GPS-4251: 2.5A																	
GPS-4303 8V ~ 15V OUTPUT (CH4) GPS-4251 8V~15V OUTPUT (CH4)	Line Regulation	≤ 5mV																	
	Load Regulation	≤ 10mV																	
	Ripple & Noise	≤ 2mVrms, 5Hz ~ 1MHz																	
	Current Output	1A																	
METER	Digital	3 digits 0.5" LED display GPS-4303/4251/3303 Out ON Accuracy ± (0.5% rdg + 2 digits) GPS-4303/3303 Out OFF Accuracy ± (0.5% rdg + 8 digits) GPS-2303 Accuracy ± (0.5% rdg + 2 digits)																	
INSULATION	Chassis and Terminal	≥ DC 500V / 20MΩ																	
	Chassis and AC Cord	≥ DC 500V / 30MΩ																	
POWER SOURCE	AC 100V/120V/220V(±10%)/230V(+10%~-6%), 50/60Hz																		
ACCESSORIES	Power cord x 1, Instruction manual x 1 GPS-4303 : Test lead GTL-104 x 2, GTL-105 x 2 or GTL-203 x 2, GTL-204 x 2 GPS-4251 : Test lead GTL-105 x 4 or GTL-203 x 4 GPS-3303 : Test lead GTL-104 x 2, GTL-105 x 1 or GTL-203 x 1, GTL-204 x 2 GPS-2303 : Test lead GTL-104 x 2 or GTL-204 x 2																		
DIMENSIONS & WEIGHT	255(W) x 145(H) x 265(D) mm, Approx. 7 kg (GPS-4303/3303/2303) ; Approx. 6.3kg (GPS-4251)																		

Specifications subject to change without notice.

Order Information

GPS-4303 4-channels, 0~30V x 2 , 0~3A x 2 , Power Supply
GPS-4251 4-channels, 0~25V x 2 , 0~0.5A x 2 , Power Supply
GPS-3303 3-channels, 0~30V x 2 , 0~3A x 2 , Power Supply
GPS-2303 2-channels, 0~30V x 2 , 0~3A x 2 , Power Supply

Standard Accessories

GPS-4303-01 Including GTL-104 x 2 & GTL-105 x 2 Type of Test Lead Set
GPS-4303-02 Including GTL-203 x 2 & GTL-204 x 2 Test Lead GTL-104 : Current 4A~10A
GPS-4251-03 Including GTL-105 x 4 Test Lead GTL-105 : Current 3A
GPS-4251-04 Including GTL-203 x 4 Test Lead GTL-203 : Current 3A
GPS-3303-05 Including GTL-104 x 2 & GTL-105 x 2 Test Lead GTL-204 : Current 4A~10A
GPS-3303-06 Including GTL-203 x 2 & GTL-204 x 2
GPS-2303-07 Including GTL-104 x 2
GPS-2303-08 Including GTL-203 x 2
Instruction manual x 1
Power cord x 1

ISO-9001 & ISO-14001 CERTIFIED MANUFACTURER



GOOD WILL INSTRUMENT CO., LTD.
No. 95-11, Pao-Chung Road, Hsin-Tien City,
Taipei Hsien, Taiwan, R.O.C.
Tel: +886-2-29179188 Fax: +886-2-29179189
http://www.goodwill.com.tw
E-mail: marketing@goodwill.com.tw

U.S.A.
INSTEK CORP.
1205 John Reed Court
City of Industry, CA 91745, U.S.A.
Tel : +1-626-3366537
Fax : +1-626-3691748
http://www.instek.com

MALAYSIA
GOOD WILL Southeast Asia Sdn. Bhd.
No. 5-3-11, Hunza Complex,
Jalan Gangsa, Greenlane Heights,
11600 Penang, Malaysia
Tel : +60-4-6591988
Fax : +60-4-6591989

CHINA
GOOD WILL Instrument(Suzhou)Co.,Ltd.
NO.69, Lushan Road, Suzhou New District,
Jiangsu, China
Tel : +86-512-66617177
Fax : +86-512-66617277

PS-2303GD1BH

GPS-2303/3303/4251/4303
Multi-Output D.C. Power Supply



- 2/3/4 Multi-Independent DC Outputs
- Low Noise and Excellent Regulation
- Versatile and Safety Design



GPS-2303/3303/4251/4303 series power supply offer the choices of 2, 3 and 4 independent outputs respectively with flexible output voltage/current combination, 0.01% highly regulated power outputs and considerate safety design.

Two main outputs of 30V/3A allow the extended applications of 60V/3A and 30V/6A under series and parallel modes of GPS-2303/3303/4303. (GPS-4251 outputs: 25V/0.5A, Series: 50V/0.5A, Parallel: 25V/1A). The additional power output(s) of GPS-3303/4251/4303 meets the increasing market demand of multiple power sources. An output ON/OFF switch prevents the load devices from accidental damage during setting adjustment. To avoid fan acoustic noise in the lab, GPS-series have been designed with fan speed control feature to minimize the fan noise annoyance. The combination of accuracy, flexibility and safety makes GPS-series an all-in-one solution in a broad application range of R&D, Education Lab., Manufacturing, Service, Component Test, and System Power Module.

FEATURES :

Multiple Power Outputs

2, 3 and 4 independent isolated outputs with four "3 digit" LED displays

Stable and Clean Power

0.01% load and line regulation and low ripple and noise

Flexible Output Voltage and Current

Tracking operation and auto Series/Parallel extend application range to 60V/3A and 30V/6A (GPS-4251 Series: 50V/0.5A, Parallel: 25V/1A)

Safety Design

Output ON/OFF switch, CC/CV modes, Overload Protection and Reverse Polarity Protection

Low Fan Acoustic Noise

Fan speed control circuit to minimize Fan Noise

APPEARANCE :



GPS-2303 (2 Outputs)



GPS-3303 (3 Outputs)



GPS-4303/4251 (4 Outputs)



Optional

(European Jack Type Terminal for All Models)

Multi-Output, High Quality Power Supply With Affordable Price



GPS-2303/3303/4251/4303


GPS - 2303 2 Outputs

GPS - 3303 3 Outputs

GPS - 4251 4 Outputs

GPS - 4303 4 Outputs

Suffix code definition : GPS - X X X X



Safety Design

The output load is protected from accidental damage during output setting adjustment. The power output could be switched off for setting change, and switched on once the setting is done. The polarity protection is also available to avoid the damage of misconnection.

Stable and Clean Output

0.01% Line/Load regulation keeps power output steady in spite of power line fluctuation and load effect. The clean power with low ripple and noise ensures your jobs done without any suspicion of power source purity.

Front Panel Display

Two outputs of Voltage/Current display could be monitored on the front panel simultaneously. CH1/CH3 or CH2/CH4 of power output Voltage/Current could be selected for display by a front panel switch.

Multiple Outputs with Flexible Output Range

With the choices of multiple output models, GPS-series provide you a flexible solution to meet your job requirement within budget limit. In addition the tracking and the auto Series/Parallel features extend your application range up to 60V/3A (by Series) and 30V/6A (by Parallel) without acquiring additional power supply units. (GPS-4251 Series: 50V/0.5A, Parallel: 25V/1A)

Low Fan Acoustic Noise

Under the Low/No load condition, GPS-series automatically lower the fan speed to eliminate annoying acoustic noise through a thermal control circuit.

Compact, Reliable and Affordable Price

The compact design of GPS-series adopting SMD components and ring transformer has significantly reduced the size and weight of a power supply. The design advancement also makes high reliability and affordable price come together with a product.

European Jack Type Terminal

In addition to the general banana terminals, GPS-series also offer an option of European Jack Type terminals, which fulfill the market demands in Europe.

